

Beghelli code	Description	Base	Power	Fluorescent Replacement	Ballast type	Compatible Ballast	Not Compatible Ballast
56500	LED PL 10W	2G11	10	18	Conventional/Electronic	Osram QTP Optimal 1x18-40	
56501	LED PL 16W	2G11	16	24	Conventional/Electronic	Osram QTP Optimal 1x18-40 Osram QTP-M 1x26-42 Osram QTP-Optimal 2x18-40	
56502	LED PL 20W	2G11	20	36	Conventional/Electronic		Philips HF-P 236 PL-L III IDC
56503	LED PL 32W	2G11	32	55	Electronic	Helvar EL2x55s Osram Quicktronic Professional QTP-DL 2x55 GII Beghelli ST6585 258 T8 order code 292614006	Philips HF-P 255 PL-L
	LED T9 15W	GR10q	15	22	Conventional/Electronic		
	LED T9 20W	GR10q	20	32	Conventional/Electronic		
	LED T9 32W	GR10q	32	40	Conventional/Electronic		
56504	LED Compact D 10W	G24d	10	18	conventional		
56505	LED Compact D 14W	G24d	14	26	conventional		
56506	LED Compact D/E 10W	G24q	10	18	electronic		
56507	LED Compact D/E 14W	G24q	14	26	electronic		

Note: In generale le versioni funzionanti con ballast elettronici non sono adatte a funzionare con ballast adattativi (cioè quelli progettati per funzionare non con una singola potenza ma in un range di potenze) in quanto i ballast adattativi hanno un sistema di protezione che interviene

In generale le versioni funzionanti con ballast induttivo (quindi 3 modelli PL LED e i 2 modelli D LED) non sono adatti per funzionare nelle configurazioni multiple (2 tubi in serie, 4 tubi in serie e così via)